



**Problem 1 (20 points)**

Suppose  $x(t) = y(t) \cos(\omega_o t + \Theta)$ , where:  $y(t)$  is a wide-sense stationary (WSS) process with mean  $\mu_y$  and autocovariance function  $C_{yy}(\tau)$ ;  $\omega_o$  is a known constant; and  $\Theta$  is a random variable that is independent of  $y(\cdot)$  and is uniformly distributed in the interval  $[0, 2\pi]$ . Do part (a) below especially carefully, because (b) and (c) depend on it to some extent!

You might find it helpful in one or more parts of the problem to recall that

$$\cos(A) \cos(B) = \frac{1}{2} [\cos(A + B) + \cos(A - B)] .$$

- (a) (8 points) Find the mean  $\mu_x(t)$  and autocorrelation function  $E[x(t + \tau)x(t)]$  of the process  $x(\cdot)$ . Also find the cross-correlation function  $E[y(t + \tau)x(t)]$ . Explain precisely what features of your answers tell you that: (i)  $x(\cdot)$  is a WSS process; and (ii)  $x(\cdot)$  and  $y(\cdot)$  are jointly WSS.
- (b) (6 points) Suppose  $C_{yy}(\tau) = e^{-|\tau|}$  and  $\mu_y \neq 0$ . Obtain an expression for the power spectral density (PSD)  $S_{yy}(j\omega)$  in this case, and draw a *fully labeled* sketch of it. Also obtain an expression for the PSD  $S_{xx}(j\omega)$ , and draw a fully labeled sketch of it.
- (c) (6 points) With the properties of  $y(t)$  specified as in (b), is  $y(t)$  ergodic in mean value? Be sure to give a reason for your answer! Also, is  $x(t)$  ergodic in mean value? Again, describe your reasoning. If you are able to evaluate either of the following integrals on the basis of your answers here, please do so:

$$\lim_{T \rightarrow \infty} \frac{1}{2T} \int_{-T}^T y(t) dt ,$$

$$\lim_{T \rightarrow \infty} \frac{1}{2T} \int_{-T}^T y(t) \cos(\omega_o t + \Theta) dt ,$$

where  $y(t)$  and  $\Theta$  here should be interpreted as the specific values taken by these quantities in a particular experiment (we could have used other symbols, but it would have required more notational effort and may not have ended up any clearer!).

**Problem 2 (30 points)**

Let  $y[n]$  be a wide-sense stationary (WSS) process with autocorrelation function

$$R_{yy}[m] = 9\left(\delta[m] - \alpha\delta[m-1] - \alpha\delta[m+1]\right).$$

where  $\alpha > 0$ .

- (a) (3 points) What is the largest value  $\alpha$  can take? Explain your reasoning. If  $\alpha$  is increased towards its maximum value, does the power of the signal shift to lower or higher frequencies?
- (b) (4 points) Determine the following (expressed in terms of  $\alpha$ , if necessary):
  - (i)  $E\{y[n]\}$  and  $E\{y^2[n]\}$ ;
  - (ii) the correlation coefficient  $\rho$  between  $y[4]$  and  $y[5]$ .
- (c) (4 points) Suppose we are told that we will be given the measurement  $y[4]$ , and we want to find the linear minimum mean-square-error (LMMSE) estimator of  $y[5]$  in terms of  $y[4]$ . Find the estimator, and determine the associated (minimum) mean square error (MSE).
- (d) (8 points) Suppose  $x[n] = y[n] + w[n]$ , where  $w[n]$  is a white process that is uncorrelated with  $y[\cdot]$  and has power spectral density  $S_{ww}(e^{j\Omega}) = 9\alpha^2$ . Determine the power spectral density  $S_{xx}(e^{j\Omega})$  and show that it can be written in the form

$$S_{xx}(e^{j\Omega}) = K(1 - \beta e^{-j\Omega})(1 - \beta e^{j\Omega})$$

for  $K$  and  $\beta$  that you should determine (expressed in terms of  $\alpha$ , if necessary). Also determine the cross-power spectral density  $S_{yx}(e^{j\Omega})$  in terms of  $\alpha$ .

- (e) (5 points) Determine the frequency response  $H(e^{j\Omega})$  of the noncausal Wiener filter that produces the LMMSE estimate  $\hat{y}[n]$  of  $y[n]$  in terms of measurements of the entire process  $x[\cdot]$ .
- (f) (6 points) Determine the frequency response  $G(e^{j\Omega})$  of the *causal* Wiener filter that at time  $n$  uses measurements of  $x[k]$  for all present and past times  $k \leq n$  to produce an LMMSE prediction of the *measurement* at the next step, i.e., an LMMSE estimate  $\hat{x}[n+1]$  of  $x[n+1]$ . Also determine the associated MSE.